2X-LB

Ringkarte für 2X-F2-FB-04, Erweiterung um 2 Ringe

Übersicht

Ringkarte - Erweiterung um 2 Ringe - für 2X-F2-FB-04 / 2010-2FB - Ruhestrom (ohne Melder) / Ausgangsalarmstrom
120mA / 250mA bei 24 V / 36 V - Redundanzprozessor je Ring

The Application

The loop board allows for bigger single panel applications. Instead of using two 2-loop panels you now have only one panel to power and all the loop wiring is concentrated to one location without having to use a Firenet network.

In case you need to expand an existing system you don't need to put another panel in place. You only have to add the loop board. This makes your system more flexible and easier to expand.

Please note that only the 2-loop panel has this capability of adding the additional loop board.

Mounting

The board can be plugged directly on the front of the main board of the panel on the easy to remove chassis. No additional cabling needs to be done.



Einzelheiten

- 2 Ringe
- 4 frei programmierbare Ausgänge

2X-LB

Ringkarte für 2X-F2-FB-04, Erweiterung um 2 Ringe

Technische Spezifikationen

General

Maximum system capacity (device count)	up to 256

Loop

Maximum loop capacity	2

Zone

Maximum zone capacity	up to 256

Physical

Form factor	Large
Mounting type	Surface mount

Regulatory

Compliancy	CPD, RoHS, WEEE
Certification	EN54-13, EN54-2, EN54-21, EN54-4

KIDDE COMMERCIAL

Als innovatives Unternehmen behält sich Kidde Global Solutions das Recht vor, Produktspezifikationen ohne Ankündigungen zu ändern. Für die aktuellsten Produktspezifikationen, besuchen Sie bitte de.firesecurityproducts.com online oder kontaktieren Sie bitte unsere Vertriebsmitarbeiter.