# AS620RF-TR-N

## Spare transceiver unit for AS620RF-N, 868 Mhz

The AS620RF-TR-N is a spare transceiver module with housing and compatible with the AS620RF-N wireless siren. The unit is intended for indoor installation. The transceiver is able to control up to 4 wireless sirens and to receive and manage all information coming from the memorized sirens.

The transceiver features inputs and outputs to interface with an alarm control panel, along with buttons, LEDs, and a display for programming and fault indication.

Optionally, up to 4 remote controls can be added to allow the end-user to operate additional outputs through his security system in a quick and easy way.



## Details

- Spare transceiver for AS620-RF-N
- Two-way wireless communication
- Plastic housing with tamper protection
- In- and outputs to be used in conjunction with any alarm control panel
- Two 7-segment displays for fault indication and programming

# AS620RF-TR-N

## Spare transceiver unit for AS620RF-N, 868 Mhz

## Technical specifications

### Electrical

| | |
|---|---|
| Operating voltage | 12 VDC |
| Current consumption | 50 mA (maximum)<br>10 mA (nominal) |

### Physical

| | |
|---|---|
| Physical dimensions | 155 x 100 x 50 mm |
| Shipping weight | 165 g |

### Environmental

| | |
|---|---|
| Operating temperature | -10 to +50°C |

### General

| | |
|---|---|
| Operating frequency | 868 MHz |
| Maximum power output | 10 mW |
| Wireless signal range | 500 m |
| Compatability | AS620RF-N, AS620RF-RC |

As a company of innovation, Kidde Global Solutions reserves the right to change product specifications without notice. For the latest product specifications, visit firesecurityproducts.com online or contact your sales representative.

Last updated on 21 January 2026 - 19:51